

ACK 42 CHAIN MOTORS

THE 230v ACK 42 CHAIN MOTOR IS FITTED WITH A THREE CORE CABLE

CONNECT AS FOLLOWS

BLACK WIRE OPEN

BLUE OR GREY WIRE NEUTRAL

BROWN WIRE CLOSE

ALWAYS FIT MOTOR WITH SCREWS FACING VENT BRACKET

THIS MOTOR IS FITTED WITH AN ADJUSTABLE OPENING



TO ALTER THE AMOUNT THAT THE CHAIN EXTENDS TURN THE DIAL ON THE MOTOR BODY TO THE REQUIRED SETTING. DO NOT AUTOMATICALLY SET TO 40cm! A SHORTER CHAIN EXTENSION MAY BE PREFERABLE ESPECIALLY IF THE VENT IS LARGE.

THE MOTOR IS ALSO FITTED WITH A LIMIT SWITCH. YOU MUST ADJUST THE THREADED END OF THE CHAIN SO THAT THE MOTOR SWITCHES OFF AT THE SAME TIME AS THE WINDOW REACHES ITS CLOSED POSITION.



HAVING MADE THE NECESSARY ADJUSTMENTS IT IS ESSENTIAL THAT YOU ENSURE THE CHAIN IS SQUARE TO THE MOTOR BODY AND THE LOCK NUT IS TIGHT. FAILURE TO DO THIS MAY CAUSE THE CHAIN TO TWIST AND COLLAPSE! FAILURE TO CORRECTLY ADJUST YOUR MOTOR DURING INSTALLATION WILL RESULT IN MOTOR DAMAGE, WHICH IS NOT COVERED BY THE WARRANTY!